



Modular Matrix Switcher

FDX-S16U

The FDX-S16U is an HDCP 2.2-compliant modular digital matrix switcher that supports resolutions up to 4K@60. It provides up to 16 inputs and 16 outputs. Video and embedded audio can be switched simultaneously.

With audio boards, input digital audio signals can be converted into output analog audio or Dante network audio signals. Input analog audio signals and Dante network audio signals can be converted into digital audio signals and embedded to desired output video channels.

The FDX-S16U features RS-232C/LAN ports for remote control, redundant power supply, and system check that outputs an alarm in case an abnormality is detected in power supply voltage, fans, internal temperature, or board.

The redundant power supply ensures constant availability and minimizes the chance of a failure even for mission-critical environments.

■ Specification

| Item | | Description | |
|----------------------|-------------------|--|--|
| Input board | | 4 slots (Up to 16 inputs) | |
| Output board | | 4 slots (Up to 16 outputs) | |
| Audio board | | 1 slot (Up to 32 stereo channels) | |
| Transmission | Video | Up to 4K@60 (4:4:4) | |
| signal | Audio | Multi-channel LPCM up to 8 channels | |
| Signal | Control | Up to 38.4 kbps of RS-232C, Up to 100Base-TX of LAN | |
| Instant Alert output | | 1 port/captive screw (2-pin) Non-voltage contact input up to DC 24 V 300 mA | |
| mstant Alen outp | ut | Monitoring power supply voltage, fans, internal temperature, board, and audio board status | |
| Control | RS-232C | 1 port/captive screw (3-pin), full duplex, up to 38.4 kbps | |
| Control | LAN | 1 port/RJ-45 10Base-T/100Base-TX (Auto Negotiation), Auto MDI/MDI-X | |
| | | I/O board, audio board, CPU board, fan unit, and power unit can be replaced without removing from rack, | |
| Functions | | Preset memory (32 settings), Last memory, Button security lockout, System check, | |
| | | WEB browser control, Status notification, HDBaseT status display | |
| | Power | 100 - 240 VAC ±10%, 50 Hz/60 Hz ±3 Hz | |
| | Power consumption | About 30 Watts | |
| General | Dimensions | 16.9 (W) x 5.2 (H) x 15.7 (D)" (430 (W) x 132 (H) x 400 (D) mm) (3U high) (Excluding connectors and the like) | |
| | Weight | 26.9 lbs. (12.2 kg) (With redundant power supply: 28.9 lbs. (13.1 kg)) | |
| | Temperature | Operating: 32°F to 104°F (0°C to +40°C) Storage : -4°F to +176°F (-20°C to +80°C) | |
| | Humidity | Operating/Storage: 20% to 90% (Non Condensing) | |

■ I/O hoards

| Item | Parts Number | Description |
|--------------|--------------|---|
| | FDX-SIV4UH | 4 inputs 4K@60 HDCP 2.2 HDMI/DVI |
| | FDX-SIV4UT | 4 inputs 4K@60 HDCP 2.2 HDBaseT |
| Input board | FDX-SIV4US | 4 inputs 12G-SDI/6G-SDI/3G-SDI/HD-SDI |
| | FDX-SIV4UC | 4 inputs 4K@60 HDCP 2.2 SDVoE |
| | FDX-SIV4S | 4 inputs 3G-SDI/HD-SDI/SD-SDI |
| | FDX-SOV4UH | 4 outputs 4K@60 HDCP 2.2 HDMI/DVI |
| | FDX-SOV4UT | 4 outputs 4K@60 HDCP 2.2 HDBaseT |
| | FDX-SOV4US | 4 outputs 12G-SDI/6G-SDI/3G-SDI/HD-SDI |
| utnut board | FDX-SOV4UC | 4 outputs 4K@60 HDCP 2.2 SDVoE |
| Output board | FDX-SOV2UHS | 2 outputs 4K@60 HDCP 2.2 HDMI/DVI scan converter |
| | FDX-SOV1UHM | 1 output 4K@60 HDCP 2.2 HDMI/DVI scan converter multiview |
| | FDX-SOV4HS | 4 outputs 1080p HDCP 1.4 HDMI/DVI scan converter |
| | FDX-SOV4TS | 4 outputs 1080p HDCP 1.4 HDBaseT scan converter |


Audio board


| Item | Parts Number | Description |
|-------------|--------------|--|
| Audio board | FDX-SAB4A | 4 inputs Unbalanced 4 outputs Balanced/Unbalanced |
| Audio board | FDX-SOA12A | 12 outputs Unbalanced |
| | FDX-SAB64D | 1 input/output 64 Dante protocol channels (32 stereo channels) |

Redundant nower supply unit

| Redundant power supply dink | | | | |
|-----------------------------|--------------|--|--|--|
| Item | Parts Number | Description | | |
| Redundant power supply unit | FDX-SRP16 | Redundant power unit with two independent power connectors | | |

■ Front & Rear Panels





This drawing (rear) is an example.

[•] All specifications and drawings are subject to change without notice. • Please do not use the supplied AC adapter and power supply cable for other products. • Audinate®, the Audinate logo and Dante are trademarks of Audinate Pty Ltd. ◆HDBaseT™ and the HDBaseT Alliance Logo are trademarks of the HDBaseT Alliance Logo are trademarks of the HDBaseT Alliance. ◆The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc. in the United States and other countries.

◆SDVoE™ and SDVoE logo are trademarks of SDVoE Alliance. ◆All other company and product names mentioned in this document are either registered trademarks of their respective owners. In this document, the "®" or "™" marks may not be specified. ◆©2020 IDK Corporation, all rights reserved.